

YOUR  
SMART  
ENERGY



# 便携式 储能电源

BlackBee 2000  
2200 W / 2203.2 Wh / 21 kg



\*有 5 种交流插头标准可用。(不可在一台设备中混合使用)



双向逆变

UPS

94V0阻燃外壳

两个无线充电器

两路动态扫描MPPT

2200W连续输出功率

同时可为15台设备充电

# BlackBee 2000



型号	
BlackBee 2000	
基本参数	
容量	2,203.2 Wh
逆变效率	95%
电池类型	锂离子电芯
工作温度	-10 ~ 45°C
存储温度	-30 ~ 55°C
尺寸(长 x 宽 x 高)	438 x 340 x 283 mm
保修	2年
重量	21 kg
电气参数	
DC (光伏) 输入 (安德森) x 2	11V-45V, 单口最大400W
AC输入 x 1	220V / 50Hz UPS模式最大3600W, 仅充电最大1800W
额定输出功率	AC:2200W DC:380 W
峰值输出功率	3300W (15秒)
USB输出 x 6	USB-C x 2, PD100W 每个 (5V ===3A; 9V ===3A; 12V ===3A; 15V ===3A; 20V ===5A)
	USB-A x 4, QC24W 每个 (5V ===3 A; 9V ===2.6A; 12V ===2A)
DC输出 (5525) x 2	12V ===5A; 12V ===3A
车充输出 x 1	12V ===10A
AC 输出 x 4	220VAC, 50Hz, 纯正弦波
	连续输出功率2200W, 峰值: 3300W
无线充 x 2	10 W x 2

#### 中国总公司

☎ +86 513 8060 6891  
✉ info@alpha-ess.com  
🌐 www.alphaess.com  
📍 江苏省南通市高新区九华路888号

#### 苏州分公司

☎ +86 512 6828 7609  
✉ info@alpha-ess.com  
🌐 www.alphaess.com  
📍 江苏省苏州市吴中区太湖东路  
运河小镇总部产业园10栋A楼

#### 欧洲子公司

☎ +49 610 3459 1601  
✉ europe@alpha-ess.de  
🌐 www.alphaess.de  
📍 Paul-Ehrlich-Straße 1a, Langen,  
Hessen D-63225 Germany

#### 澳洲子公司

☎ +61 02 9000 7676  
✉ Australia@alpha-ess.com  
🌐 www.alphaess.com  
📍 8/15-21 Gibbes Street, Chatswood,  
NSW 2067 Australia

#### 意大利子公司

☎ +39 339 462 4288  
✉ info@alpha-ess.it  
🌐 www.alphaess.com  
📍 Via Don Minzoni, 17,  
Calenzano Firenze 50041 Italy

#### 英国子公司

☎ +44 145 354 5222  
✉ info@alpha-ess.com  
📍 Drake house, Long  
street, Dursley, gl11  
4hh UK

#### 新加坡子公司

☎ +65 6513 1125 / +65 6513 1126  
✉ Singapore@alpha-ess.com  
📍 2 Corporation Road #01-06A  
Corporation Place 618494  
Singapore

#### 美国子公司

☎ +1 408 368 7828  
✉ usa@alpha-ess.com  
📍 Unit 5 2180 S Ivanhoe  
St, Denver, CO 80222  
USA

#### 韩国子公司

✉ info@alpha-ess.com  
📍 2F, 19-4, Nohyeong 11-gil,  
Jeju-si, Jeju-do, Republic of  
Korea


YOUR  
SMART  
ENERGY



# PORTABLE POWER STATION

## BlackBee 2000

2200 W / 2203.2 Wh / 23 kg



\*There are 5 AC plug standards available. (NOT mixable in one device)



**Bidirectional Inverter**

**Uninterrupted Power Supply**

**94V0 Flame-Retardant Casing**

**2 Wireless Charging Pads**

**Dual Dynamic MPPT**

**2200W Output Power**

**Charge up to 15 Devices Simultaneously**

# BlackBee 2000



Model	BlackBee 2000
<b>Basic Parameters</b>	
Nominal Energy	2,203.2 Wh
Inverter Efficiency	95%
Battery Type	Lithium Ion
Operating Temperature for Charging	14-113°F(-10-45°C)
Operating Temperature for Discharging	14-113°F(-10-45°C)
Dimension (L x W x H)	438 x 340 x 283 mm
Warranty	2 Years
Weight	50.7lbs (23 kg)
<b>Electrical Parameters</b>	
DC (Solar) Input (Anderson) x 2	11V-45 V, 10 A / 300 W MAX each
AC Input x 1	100-120 V, 200-240 V
Rate Output Power	AC:1600 W DC:440 W
Peak Output Power	3000 W
USB Port x 6	USB-C x 2, PD60 W each(5 V=3 A; 9 V=3 A; 12 V=3 A; 15 V=3 A; 20 V=3 A)
	USB-A x 4, QC3.0 36 W each(5 V=3 A; 9 V=3 A; 12 V=3 A; 15 V=2.4 A; 20 V=1.8 A)
DC Port (5525) x 2	12V=5 A; 12V=3A
Car Port x 1	12V=10A
AC Port x 4	100-240 VAC, 50 / 60 Hz, Pure Sine Wave
	1600 W Continuous, 3000 W Peak
Wireless Charging x 2	10 W x 2

\*You can have 2 X 300 W panels as long as the voltage current will not exceed 10 A and total input will not exceed 600 W.

#### Alpha ESS Co., Ltd.

+86 513 8060 6891  
 info@alpha-ess.com  
 www.alphaess.com  
 Jiuhua Road 888, Nantong High-Tech Industrial Development Zone, Nantong, Jiangsu Province, China

#### Alpha ESS Suzhou Co., Ltd.

+86 512 6828 7609  
 info@alpha-ess.com  
 www.alphaess.com  
 Building 10-A, Canal Town Industrial Park, 99 Taihu E Rd, Wuzhong District, Suzhou, Jiangsu Province, China

#### Alpha ESS Europe GmbH

+49 610 3459 1601  
 europe@alpha-ess.de  
 www.alphaess.de  
 Paul-Ehrlich-Straße 1a, Langen, Hessen D-63225 Germany

#### Alpha ESS Australia Pty. Ltd.

+61 02 9000 7676  
 Australia@alpha-ess.com  
 www.alphaess.com  
 8/15-21 Gibbes Street, Chatswood, NSW 2067 Australia

#### Alpha ESS Italy S.r.l.

+39 339 462 4288  
 info@alpha-ess.it  
 www.alphaess.com  
 Via Don Minzoni, 17, Calenzano Firenze 50041 Italy

#### Alpha ESS UK Ltd.

+44 145 354 5222  
 info@alpha-ess.com  
 Drake house, Long street, Dursley, gl11 4hh UK

#### Alpha ESS International Pte. Ltd.

+65 6513 1125 / +65 6513 1126  
 Singapore@alpha-ess.com  
 2 Corporation Road #01-06A Corporation Place 618494 Singapore

#### Alpha ESS USA, Inc.

+1 408 368 7828  
 usa@alpha-ess.com  
 Unit 5 2180 S Ivanhoe St, Denver, CO 80222 USA

#### Alpha ESS Korea Co., Ltd.

info@alpha-ess.com  
 2F, 19-4, Nohyeong 11-gil, Jeju-si, Jeju-do, Republic of Korea