

YOUR  
SMART  
ENERGY



# 便携式 储能电源

BlackBee 1000  
1000 W / 1036 Wh / 10.2 kg



\*有 4 种交流插头标准可用。(不可在一台设备中混合使用)



支持无线充电

狂野&实用的设计

配备 SOS / 应急灯

94V0标准阻燃外壳

轻便, 带可折叠手柄

内置MPPT控制器

1036Wh大容量锂离子电池

支持最多12台设备同时工作

# BlackBee 1000



BlackBee 1000	
<b>基本参数</b>	
额定能量	1036 Wh
额定容量	288,000 mAh
电芯类型	锂离子
充电温度范围	0 ~ 40 °C
放电温度范围	-10 ~ 40 °C
尺寸 (长 x 宽 x 高)	343 x 254 x 266 mm
质保	2 年产品质保
重量	10.2 kg
<b>电气性能参数</b>	
直流输入	12 - 24 V (200 W MAX)
USBC 输入	PD100 W (5 V / 3 A; 9 V / 3 A; 12 V / 3 A; 15 V / 3 A; 20 V / 5 A)
额定输出功率	1000 W
峰值输出功率	2000 W
交流输出 x 3	3 x 220 V / 50 Hz
车充输出 x 1	1 x 12 V / 10 A
USBC 输出 x 2	Output 1: PD100 W (5 V / 3 A; 9 V / 3 A; 12 V / 3 A; 15 V / 3 A; 20 V / 5 A)
	Output 2: 5 V / 3 A
USBA 输出 x 2	Output 1: 5 V / 2.4 A
	Output 2: 5 V / 2.4 A
无线充电 x 2	10 W x 2

中国总公司  
☎ +86 513 8060 6891  
✉ info@alpha-ess.com  
🌐 www.alphaess.com  
📍 江苏省南通市高新区九华路888号

苏州分公司  
☎ +86 512 6828 7609  
✉ info@alpha-ess.com  
🌐 www.alphaess.com  
📍 江苏省苏州市吴中区太湖东路  
运河小镇总部产业园10栋A楼

欧洲子公司  
☎ +49 610 3459 1601  
✉ europe@alpha-ess.de  
🌐 www.alphaess.de  
📍 Paul-Ehrlich-Straße 1a, Langen,  
Hessen D-63225 Germany

澳洲子公司  
☎ +61 02 9000 7676  
✉ Australia@alpha-ess.com  
🌐 www.alphaess.com  
📍 8/15-21 Gibbes Street, Chatswood,  
NSW 2067 Australia

意大利子公司  
☎ +39 339 462 4288  
✉ info@alpha-ess.it  
🌐 www.alphaess.com  
📍 Via Don Minzoni, 17,  
Calenzano Firenze 50041 Italy

英国子公司  
☎ +44 145 354 5222  
✉ info@alpha-ess.com  
📍 Drake house, Long  
street, Dursley, gl11  
4hh UK

新加坡子公司  
☎ +65 6513 1125 / +65 6513 1126  
✉ Singapore@alpha-ess.com  
📍 2 Corporation Road #01-06A  
Corporation Place 618494  
Singapore

美国子公司  
☎ +1 408 368 7828  
✉ usa@alpha-ess.com  
📍 Unit 5 2180 S Ivanhoe  
St, Denver, CO 80222  
USA

韩国子公司  
☎ info@alpha-ess.com  
📍 2F, 19-4, Nohyeong 11-gil,  
Jeju-si, Jeju-do, Republic of  
Korea

YOUR  
SMART  
ENERGY



# PORTABLE POWER STATION

**BlackBee 1000**  
1000 W/1036 Wh/10.2 kg



\*There are 4 AC plug standards available. (NOT mixable in one device)



- Support Wireless Charging
- Attractive & Practical Design
- SOS / Emergency Lights
- 94V0 Flame-Retardant Casing
- Easy to Carry with a Foldable Handle
- Built-in MPPT Controller
- 1036Wh Li-ion Battery
- Charge up to 12 Devices Simultaneously



# BlackBee 1000



Model	BlackBee 1000
<b>Basic Parameters</b>	
Nominal Energy	1036 Wh
Battery Type	Li-ion
Operating Temperature for Charging	0 ~ 40 °C
Operating Temperature for Discharging	-10 ~ 40 °C
Dimension (L x W x H)	340 x 255 x 270 mm
Warranty	2 Years
Weight	10.2 kg
<b>Electrical Parameters</b>	
DC Input	12 V - 24 V ( 180 W MAX )
USB C Input	PD100 W ( 5 V / 3 A; 9 V / 3 A; 12 V / 3 A; 15 V / 3 A; 20 V / 5 A )
Rate Output Power	1000 W
Peak Output Power	2000 W
AC Output	230 V / 50 Hz
Car Port Output	1 x 12 V / 10 A
USBC Output	Output 1: PD100 W ( 5 V / 3 A; 9 V / 3 A; 12 V / 3 A; 15 V / 3 A; 20 V / 5 A )
	Output 2: 5 V / 3 A
USBA Output	Output 1: 5 V / 2.4 A
	Output 2: 5 V / 2.4 A
Wireless Charging	2 x Wireless Charging ( Single 10 W; Total 15 W )
LED Light	3W, 6500K, >300LM

\* You can have 2 X 100W panels as long as the voltage current will not exceed 10A and total input will not exceed 200W.

#### Alpha ESS Co., Ltd.

☎ +86 513 8060 6891  
 ✉ info@alpha-ess.com  
 🌐 www.alphaess.com  
 📍 Jiuhua Road 888, Nantong High-Tech Industrial Development Zone, Nantong, Jiangsu Province, China

#### Alpha ESS Suzhou Co., Ltd.

☎ +86 512 6828 7609  
 ✉ info@alpha-ess.com  
 🌐 www.alphaess.com  
 📍 Building 10-A, Canal Town Industrial Park, 99 Taihu E Rd, Wuzhong District, Suzhou, Jiangsu Province, China

#### Alpha ESS Europe GmbH

☎ +49 610 3459 1601  
 ✉ europe@alpha-ess.de  
 🌐 www.alphaess.de  
 📍 Paul-Ehrlich-Straße 1a, Langen, Hessen D-63225 Germany

#### Alpha ESS Australia Pty. Ltd.

☎ +61 02 9000 7676  
 ✉ Australia@alpha-ess.com  
 🌐 www.alphaess.com  
 📍 8/15-21 Gibbes Street, Chatswood, NSW 2067 Australia

#### Alpha ESS Italy S.r.l.

☎ +39 339 462 4288  
 ✉ info@alpha-ess.it  
 🌐 www.alphaess.com  
 📍 Via Don Minzoni, 17, Calenzano Firenze 50041 Italy

#### Alpha ESS UK Ltd.

☎ +44 145 354 5222  
 ✉ info@alpha-ess.com  
 📍 Drake house, Long street, Dursley, gl11 4hh UK

#### Alpha ESS International Pte. Ltd.

☎ +65 6513 1125 / +65 6513 1126  
 ✉ Singapore@alpha-ess.com  
 📍 2 Corporation Road #01-06A Corporation Place 618494 Singapore

#### Alpha ESS USA, Inc.

☎ +1 408 368 7828  
 ✉ usa@alpha-ess.com  
 📍 Unit 5 2180 S Ivanhoe St, Denver, CO 80222 USA

#### Alpha ESS Korea Co., Ltd.

☎ info@alpha-ess.com  
 📍 2F, 19-4, Nohyeong 11-gil, Jeju-si, Jeju-do, Republic of Korea